

## Rozbočovací svorky HLAK 25



2941

6531

6532

6530

2942

2990

Obj. číslo	Název	Barva	Počet pólů	Vstup	Výstup	Rozměry (mm)	Jm. proud (A)	Napětí U (V AC/DC)	Bal./ks
6510	HLAK 25//1 C L 080110-0-4		1	2x25 mm <sup>2</sup>	2x16 mm <sup>2</sup>	49,3 x 24,8 x 55,7	100	1000	5
6530	HLAK 25//1 C N 080110-1-4		1	2x25 mm <sup>2</sup>	2x16 mm <sup>2</sup>	49,3 x 24,8 x 55,7	100	1000	5
6520	HLAK 25//1 C PE 080110-2-4		1	2x25 mm <sup>2</sup>	2x16 mm <sup>2</sup>	49,3 x 24,8 x 55,7	100	1000	5
6531	HLAK 25//1 C LB 080110-3-4		1	2x25 mm <sup>2</sup>	2x16 mm <sup>2</sup>	49,3 x 24,8 x 55,7	100	1000	5
6532	HLAK 25//1 C LS 080110-4-4		1	2x25 mm <sup>2</sup>	2x16 mm <sup>2</sup>	49,3 x 24,8 x 55,7	100	1000	5
2941	HLAK 25//3 C L 080130-0-4		3	6x25 mm <sup>2</sup>	6x16 mm <sup>2</sup>	49,3 x 63,5 x 55,7	100	1000	2
2942	HLAK 25//3 C LNPE 080130-1-4		3	6x25 mm <sup>2</sup>	6x16 mm <sup>2</sup>	49,3 x 63,5 x 55,7	100	1000	2
2945	HLAK 25//3 C 2LPE 080130-4-4		3	6x25 mm <sup>2</sup>	6x16 mm <sup>2</sup>	49,3 x 63,5 x 55,7	100	1000	2
4210	HLAK 25//4 C 4L 080140-0-4		4	8x25 mm <sup>2</sup>	8x16 mm <sup>2</sup>	49,3 x 78,6 x 55,7	100	1000	1
4211	HLAK 25//4 C 3LN 080140-1-4		4	8x25 mm <sup>2</sup>	8x16 mm <sup>2</sup>	49,3 x 78,6 x 55,7	100	1000	1
4212	HLAK 25//4 C 3LPE 080140-3-4		4	8x25 mm <sup>2</sup>	8x16 mm <sup>2</sup>	49,3 x 78,6 x 55,7	100	1000	1
4214	HLAK 25//4 C PE3L 080140-4-4		4	8x25 mm <sup>2</sup>	8x16 mm <sup>2</sup>	49,3 x 78,6 x 55,7	100	1000	1
2830	HLAK 25//5 C 5L 080150-0-4		5	10x25 mm <sup>2</sup>	10x16 mm <sup>2</sup>	49,3 x 95,9 x 55,7	100	1000	1
2990	HLAK 25//5 C 3LNPE 080150-1-4		5	10x25 mm <sup>2</sup>	10x16 mm <sup>2</sup>	49,3 x 95,9 x 55,7	100	1000	1
2991	HLAK 25//5 C N3LPE 080150-2-4		5	10x25 mm <sup>2</sup>	10x16 mm <sup>2</sup>	49,3 x 95,9 x 55,7	100	1000	1
2992	HLAK 25//5 C PE3LN 080150-3-4		5	10x25 mm <sup>2</sup>	10x16 mm <sup>2</sup>	49,3 x 95,9 x 55,7	100	1000	1
2993	HLAK 25//5 C PEN3L 080150-4-4		5	10x25 mm <sup>2</sup>	10x16 mm <sup>2</sup>	49,3 x 95,9 x 55,7	100	1000	1

